



Overview

- The 6030 programmable timer is suitable for most functions that require a timed operation e.g. Applications, Siren/Bell Cut Off Module, Dialer Delay, Guard Tour Supervisory Timer, Pulsar / Flasher, etc.



Specifications

- | | |
|---|--|
| <ul style="list-style-type: none"> • 6VDC or 12VDC operation is selectable. • Form "C" relay contacts are 5 amp at 120VAC/28VDC. • Current draw stand by 3mA relay energizes at 75mA. • Quick and extremely accurate time range adjustment from 1 second to 60 minutes. | <ul style="list-style-type: none"> • LED indicates relay is energized. • Repeat (flasher/pulse) mode. • Relay activates at the end of the timing cycle. |
|---|--|

Board Dimensions (approximate)

3"L x 2.5"W x .75"H

Mounting Diagram

